

Instruction Guide for HD Lockdown - (HDL) (Patent pending)

Mechanical Security for Tablets

(Code 840-015)



1. Locate HD Lockdown (HDL) assembled unit, twin stud washer, 2 wingnuts, Lg top bracket optional, white plastic spacer, and lock keys.



2. Insert the device's charging cable up through the bottom of the post.



3. Feed the device's charging cable out through the hole in the front of the HDLD.



4. Set the HDLD post into the fixture's hole or track.



5. Underneath the fixture, place the twin stud washer on both bolts. Place a wingnut on each bolt. Firmly tighten the wingnuts, flush against the fixture.



6. Find the lock on the back side of the HDLD.



7. Insert a key to unlock the HDLD.



8. The lock pin is out when it is unlocked.



9. Slide the top bracket out of the HDLD.



10. Using a screwdriver, loosen all four screws in the center of the HDLD side brackets. Once loosened a few turns, the side bracket on top can slide left to right to adjust to the size of the device.



11. If necessary, the screws can be removed completely for full adjustability of both side brackets. The side brackets are marked as "TOP" and "BOTTOM" and cannot be interchanged.



12. When the size has been adjusted to fit the device, use a screwdriver to tighten down all four screws.



13. There is a point on the top edge of each side bracket. When these two points are overlapping, the side brackets will be secured at mid-range.



14. Slide the device into the HDLD from the top. Plug in the charging cable.



15. Pass the cable through the cable guide for a cleaner look.



16. Reinsert the HDLD's top bracket and slide it up against the top of the device.



17. Press the lock pin in to lock the HDLD's top bracket in place.



18. Verify that the lock pin is pressed and the top bracket will not slide out.



19. Feed any excess length of the device's charging cable down through the post into the fixture for cable management.



20. The displayed device is now mechanically secured in the HDLD.